# **PHILIPS** Lighting



# HF-Performer Intelligent for TL5 HE/HO lamps

# HF-Pi 1 28/35/49/54 TL5 EII 220-240V

HF-Performer Intelligent for Master and ECO TL5 HE/HO, TL-D and PL-L lampsHF-Performer Intelligent features automatic recognition of the connected lamp and is independently able to adjust its operation parameters exactly to the respective lamp. This results in a substantial benefit, especially for T5 lamps, as it means TL5 HE and HO lamps of the same length can be interchanged.With a choice of seven ballasts, the customer is able to handle efficiently every possible combination of Master TL5 and Eco, TL-D, and PL-L lamps.;The ballast is primarily designed for Indoor application. For outdoor application, the luminaire should be minimum Classland need to be sufficiently protected against water & dust. The installation should also be guard against any lightening surge or any other necessary electrical protection as deemed in such typical installation & application.

## **Product data**

eneral Information		Input Frequency	50 to 60
pplication Code	EII	Ignition Method	Warm Sta
/pe Version	mk1	Crestfactor (Max)	1.7
mp Type	TL5	Ignition Time (Max)	5.0 s
umber of Lamps	1 piece/unit	Mains Voltage Performance (AC)	-8%-+6%
umber of Products on MCB (16A Type B)	18	Mains Voltage Safety (AC)	-10%-+10%
Nom)		Earth Leakage Current (Max)	0.5 mA
utomatic Restart	Yes	Inrush Current Width	0.35 ms
		Constant Wattage Deviation	-2%/+2%
perating and Electrical		Ballast Factor (Nom)	1.00
nput Voltage	220 to 240 V	Power Losses (Nom)	4.8-7.0 W

# HF-Performer Intelligent for TL5 HE/HO lamps

Inrush Current Peak (Max)	20 A
Wiring	
Connector Type Input Terminals	Insert
Cable Capacity Output Wires Mutual (Nom)	70 pF
Connector Type Output Terminals	Insert
Cable Length Hot Wiring	0.75 m
Wire Striplength	8.0-9.0 mm
Input Terminal Cross Section	0.50-1.00 mm²
Output Terminal Cross Section	0.50-1.00 mm²
Cable Capacity Output Wires to Earth (Nom)	70 pF

#### System characteristics

Rated Ballast-Lamp Power	28-54 W
Rated Lamp Power on TL5	28/35/49/54 W
System Power on TL5	37.9/44.4/56.8/62.6 W
Lamp Power on TL5	30.9/39.8/52.6/57.8 W
Power Loss on TL5	7/4.6/4.2/4.8 W

_				
le	mn	era	atu	re
				-

T-Ambient (Max)	50 °C	
T-Ambient (Min)	-25 ℃	
T-Storage (Max)	80 °C	
T-Storage (Min)	-40 °C	
T-Case Lifetime (Nom)	75 °C	
T-Case Maximum (Max)	75 °C	
T-Ignition (Max)	50 ℃	
T-Ignition (Min)	-25 ℃	

### Mechanical and Housing

Housing	
Housing	

Nominal Light Output After 60 Seconds	100% of EBLF	
Battery Voltage Lamp Operation	198-276	

L360x30x22

Emergency Ballast Lumen Factor (EBLF)	100 %
(Nom)	
Nominal Light Output After 5 Seconds	50% of EBLF
Approval and Application	
Energy Efficiency Index	A2 BAT
IP Classification	IP 20 [ Ingress Protection 20]
EMI 9 kHz 30 MHz	EN55015
EMI 30 MHz 1000 MHz	EN 55022 Class B
Safety Standard	IEC 61347-2-3
Performance Standard	IEC 60929
Quality Standard	ISO 9000:2000
Environmental Standard	ISO 14001
Harmonic Current Emission Standard	IEC 61000-3-2
EMC Immunity Standard	IEC 61547
Vibration Standard	IEC68-2-6 F c
Bumps Standard	IEC 68-2-29 Eb
Humidity Standard	EN 61347-2-3 clause 11
Approval Marks	CE marking ENEC certificate VDE-EMV
	certificate
Temperature Marking	Yes
Emergency Standard	IEC 60598-2-22
Hum And Noise Level	Inaudible
Product Data	
Full product code	871150091496530
Order product name	HF-Pi 1 28/35/49/54 TL5 EII 220-240V
EAN/UPC - Product	8711500914965

913700624166


913700624166


0.247 kg

1

12

#### **Dimensional drawing**





 Product
 D1
 C1
 A1
 A2
 B1

 HF-Pi 128/35/49/54 TL5 EII
 4.2 mm
 22 mm
 360 mm
 350 mm
 30 mm

 220-240V
 22
 20
 20
 20
 20
 20
 20

HF-Pi 1 28/35/49/54 TL5 EII 220-240V

Order code

Material Nr. (12NC)

Net Weight (Piece)

Numerator - Quantity Per Pack

Numerator - Packs per outer box

HF-Performer Intelligent for TL5 HE/HO lamps



© 2020 Signify Holding All rights reserved. Signify does not give any representation or warranty as to the accuracy or completeness of the information included herein and shall not be liable for any action in reliance thereon. The information presented in this document is not intended as any commercial offer and does not form part of any quotation or contract, unless otherwise agreed by Signify. Philips and the Philips Shield Emblem are registered trademarks of Koninklijke Philips N.V.

www.lighting.philips.com 2020, November 23 - data subject to change